

MRFSTF-1842-75-1S

Stopband Cavity Filter

Electrical Properties:

NO	Items	Specifications
1	Frequency Range	1805~1880MHz
2	Rejection	≥40dB
3	VSWR	≤2.0
4	Passband Frequency Range	DC~1785MHz@1900MHz-3000MHz
5	Insertion Loss	≤2.0dB
6	Impedance	50 Ω
7	Port Connector	SMA-Female
8	Configuration	As Below

Drawing (unit mm):

